

## LED Bright Stik™ range extension



DATA SHEET

### Product information

LED Bright Stik™ illuminates spaces with light instantly. Its sleek cylindrical shape fits in place of a traditional incandescent bulb - and some sockets where a traditional bulb or CFL doesn't fit. Replace a 40W, 60W & 100W incandescent with an LED Bright Stik and keep saving for the next 15 years\*. That's a long time you can spend not worrying about light bulbs.

### Features & benefits

- LED technology for energy saving
- Redesigned shape with multiple advantages:
- To fit in more fixtures compared to CFL
- Optimised for omni-directional light distribution
- Space-saving benefits on-shelf
- 240 degree Beam angle
- Replaces a standard 40W, 60W, 75W & 100W bulb
- Rated life of 15 years\*
- 3 colour options - 3000K 4000K & 6500K
- Always ready — instant brightness
- No mercury — worry-free use and disposal

\*Based on 2.7 hours of per day use.

### Applications areas



Hospitality



Retail



Home



GE imagination at work

# Specification summary

## Multipack

Product Code	Product Description	Wattage [W]	Volts [V]	Cap	Lumen [lm]	CCT [K]	Switching Cycles	Length [mm]	Diameter [mm]
93032230	LED 6/STIK/830/100-240/B22/F 3/15	6	100-240	B22	470	3000	100 000	115	37
93023175	LED 6/STIK/830/100-240/E27/F 3/15	6	100-240	E27	470	3000	100 000	115	37
93023174	LED 6/STIK/840/100-240/E27/F 3/15	6	100-240	E27	470	4000	100 000	115	37
93032231	LED 6/STIK/865/100-240/E27/F 3/15	6	100-240	E27	470	6500	100 000	115	37
93023171	LED10/STIK/830/100-240/B22/F 3/15	9	100-240	B22	810	3000	100 000	115	37
93023173	LED10/STIK/830/100-240/E27/F 3/15	9	100-240	E27	810	3000	100 000	115	37
93023172	LED10/STIK/840/100-240/E27/F 3/15	9	100-240	E27	810	4000	100 000	115	37
93023110	LED10/STIK/865/100-240/E27/F 3/15	9	100-240	E27	810	6500	100 000	115	37
93038719	LED12/STIK/830/100-240/B22/F 2/10	12	100-240	B22	1060	3000	100 000	136	45
93038722	LED12/STIK/830/100-240/E27/F 2/10	12	100-240	E27	1060	3000	100 000	136	45
93038720	LED12/STIK/840/100-240/E27/F 2/10	12	100-240	E27	1060	4000	100 000	136	45
93038721	LED12/STIK/865/100-240/E27/F 2/10	12	100-240	E27	1060	6500	100 000	136	45
93023112	LED16/STIK/830/100-240/B22/F 2/10	15	100-240	B22	1521	3000	100 000	136	45
93023114	LED16/STIK/830/100-240/E27/F 2/10	15	100-240	E27	1521	3000	100 000	136	45
93023113	LED16/STIK/840/100-240/E27/F 2/10	15	100-240	E27	1521	4000	100 000	136	45
93023111	LED16/STIK/865/100-240/E27/F 2/10	15	100-240	E27	1521	6500	100 000	136	45

## Single pack

93024033	LED10/STIK/830/100-240/E27/F 1/15	9	100-240	E27	810	3000	100 000	115	37
93032233	LED10/STIK/840/100-240/E27/F 1/15	9	100-240	E27	810	4000	100 000	115	37
93024034	LED10/STIK/865/100-240/E27/F 1/15	9	100-240	E27	810	6500	100 000	115	37
93038839	LED12/STIK/830/100-240/E27/F 1/15	12	100-240	E27	1060	3000	100 000	136	45
93038840	LED12/STIK/840/100-240/E27/F 1/15	12	100-240	E27	1060	4000	100 000	136	45
93038841	LED12/STIK/865/100-240/E27/F 1/15	12	100-240	E27	1060	6500	100 000	136	45
93024035	LED16/STIK/830/100-240/E27/F 1/15	15	100-240	E27	1521	3000	100 000	136	45
93038843	LED16/STIK/840/100-240/E27/F 1/15	15	100-240	E27	1521	4000	100 000	136	45
93024037	LED16/STIK/865/100-240/E27/F 1/15	15	100-240	E27	1521	6500	100 000	136	45

## Operation and maintenance

- Store and use the lamps the same way as traditional lamps.
- Check your fixtures are properly wired and don't deliver voltage spike to lamps causing overheating/failure.
- Ambient temperature range -20° C to 40° C
- 240 degree Beam angle
- Lamps should be kept free from contamination.
- Good condition of the lamp-holder contacts is important to ensure proper operation of lamp.
- Ensure lamp is cool before removing.
- Switch off mains supply before installing/removing lamp.
- Non-dimmable

## Dimensions

